



# COMMAND CENTER SPECS

Measure and log concrete temperature history, calculate maturity, and evaluate in-place strength.



## SENSOR DETAILS

<b>Maturity Method</b>	Nurse-Saul or Arrhenius (ASTM C 1074)
<b>Datum Temperature/Activation Energy</b>	User Definable
<b>Sensor Accuracy</b>	+/- 1.0 °C (1.8 °F)
<b>Sensor Resolution</b>	0.5 °C (1.0 °F)
<b>Temperature Range</b>	-40.0 to 85.0 °C (-40.0 to 185.0 °F)
<b>Measurement Intervals</b>	1, 2, 5, 10, 15, 20, 30, 60 minute(s)
<b>Sensor Size</b>	1/4 inch x 3/4 inch (6.35 mm x 19.05 mm) diameter
<b>Cable Length</b>	4 ft (1.22 m), 8 ft (2.44 m), 15 ft (4.57 m), 30 ft (9.14 m), or 50 ft (15.24 m). Custom lengths available.
<b>Sensor Battery Life</b>	Warrantied for 2 years

## SOFTWARE REQUIREMENTS

<b>COMMAND Center for Windows</b>	Supported on 32 bit or 64 bit versions of Windows XP Professional SP3, Windows Vista SP1+, Windows 7, Windows 8, and Windows 10. Requires Microsoft .NET Framework 4 Client Profile.
<b>COMMAND Center for iOS</b>	Requires iOS 11.4 or later. Supported on iPhone, iPod touch, and iPad. Requires an SRM or AutoCollector to transmit data from the sensors.

Note: Windows Mobile still supported. Contact us for details.

## SRM DETAILS

<b>Battery Type</b>	Two AA
<b>Battery Life</b>	Approx. 1 month*
<b>Signal Range</b>	Approx. 10 yd (10 m)**
<b>Connectivity</b>	Bluetooth



## AUTOCOLLECTOR DETAILS

<b>Battery Type</b>	Four D cell
<b>Battery Life</b>	Approx. 1 month*
<b>Range to SRMs</b>	Approx. 100 yd (100 m)**
<b>Cellular Range</b>	Depends on local cell coverage
<b>Connectivity</b>	Cellular and Bluetooth



\*Battery life depends on many factors, including but not limited to outside temperature, data transmission frequency, and signal availability.

\*\*Signal range can vary depending on factors such as other structures obstructing signal line of sight.

## GET COMMAND CENTER TODAY

To learn more about temperature and maturity monitoring with COMMAND Center, visit [www.COMMANDCenterConcrete.com](http://www.COMMANDCenterConcrete.com) or call +1 (888) 451 6233.



Connect with us.



Proudly assembled in the USA.

© The Transtec Group, Inc. | 6111 Balcones Drive | Austin, TX 78731 USA



**COMMAND CENTER**  
CONCRETE TEMPERATURE & MATURITY SYSTEM